

Sudden Cardiac Death

Mechanisms, structural substrates, inherited arrhythmias and
clinicopathologic correlation

Dr Abu Suraih Sakhri

MBBS, MD (Pathology)

www.abusuraisakhri.com

Learning outcomes


- Define sudden cardiac death and distinguish an electrical terminal event from a myocardial lesion.
- Explain how ischemia, fibrosis and re-entry lead to lethal ventricular rhythms.
- Classify major ischemic, structural and inherited nonatherosclerotic substrates.
- Interpret the morphology, clinical clues and prevention principles.

Clinicopathologic emphasis: The heart may not show a new infarct.

Sudden death is a clinical event, not a single lesion

- The term describes an unexpected fatal cardiac event within a defined time window.
- Multiple diseases can converge on a final lethal cardiac rhythm.
- Therefore, clinical circumstances and underlying cardiac pathology must be interpreted together.

CONCEPTUAL PATHWAY — SCHEMATIC



The operational definition uses two time windows

- Death occurs within 1 hour after the onset of symptoms, when observed.
- Alternatively, the person was last known to be well within the preceding 24 hours.
- These are operational timing criteria; They do not identify the mechanism in an individual case.

SIDE-BY-SIDE DISTINCTION

Observed event

≤ 1 hour after
symptoms

Unwitnessed event

Last seen well ≤ 24
hours

A major global burden

- Approximately 325,000 cases annually in the United States.
- The corresponding worldwide estimate is 4–5 million per year.
- These are estimates reported in the supplied 11th-edition text, not newly validated surveillance data.

ANNUAL CASE ESTIMATES

325,000

United States / year


4–5 million

Worldwide / year

A lethal arrhythmia is the dominant final mechanism

- Ventricular fibrillation is the prototypical fatal rhythm.
- Asystole is another recognized electrical endpoint.
- The shared consequence is abrupt loss of effective cardiac output.

CONCEPTUAL PATHWAY — SCHEMATIC



Ventricular fibrillation and asystole are not equivalent

- In ventricular fibrillation, depolarization becomes chaotic with no effective ventricular contraction.
- In asystole, electrical activity is absent.
- Both can lead rapidly to collapse, but they differ in electrical behavior.

SIDE-BY-SIDE DISTINCTION

Ventricular fibrillation

Chaotic electrical
activity

Ineffective contraction

Asystole


No electrical activity

No effective cardiac
output

The clinical spectrum of rhythm disturbances

- A rhythm disturbance may be intermittent or sustained.
- Palpitations or a perceived racing heart can precede major events.
- Sustained loss of cardiac output causes presyncope, syncope or sudden death.


CONCEPTUAL PATHWAY — SCHEMATIC



An arrhythmia may arise at many cardiac levels

- The sinoatrial node, atrioventricular pathways and ventricular myocardium can all initiate abnormal rhythms.
- Arrhythmias are commonly grouped as supraventricular or ventricular in origin.
- The anatomical site of abnormal firing does not by itself predict lethality.

CONCEPTUAL PATHWAY — SCHEMATIC



Most fatal instability is not confined to the nodes

- Conduction-system injury can produce a serious rhythm disturbance.
- Electrically irritable myocardium away from major conducting structures.
- The ventricular muscle can therefore generate fatal activity without focal nodal destruction.

SIDE-BY-SIDE DISTINCTION

Major conduction system

Can be injured directly

Working ventricular myocardium

Frequent source of electrical irritability

Three broad substrates alter cardiac electrical stability

- Ischemia changes myocyte excitability.
- Structural remodeling, including hypertrophy and fibrosis, disrupts orderly conduction.
- Channel defects alter depolarization or repolarization without necessarily changing gross anatomy.

RELATED SUBSTRATES / COMPONENTS

Ischemia


Fibrosis / hypertrophy

Ion channel dysfunction

Gap junctions coordinate ventricular depolarization

- Neighboring cardiomyocytes transmit electrical current through gap junctions.
- Normal intercellular coupling permits an ordered wave of activation.
- Abnormal distribution or structure of junctions can destabilize conduction.


CONCEPTUAL PATHWAY — SCHEMATIC



Ischemia increases myocyte electrical irritability

- Ischemic myocardium may fire aberrantly without undergoing lethal necrosis.
- Spontaneous depolarization can recruit interconnected neighboring cells.
- These events may initiate abnormal paths of ventricular activation.


CONCEPTUAL PATHWAY — SCHEMATIC



Fibrosis creates nonuniform pathways of conduction

- Fibrotic foci interrupt direct myocyte-to-myocyte signaling.
- Current must propagate through surviving pathways with altered geometry.
- The resulting heterogeneity provides a setting for re-entry circuits.


CONCEPTUAL PATHWAY — SCHEMATIC



Re-entry sustains inappropriate ventricular activation

- An excitation wave can circulate through a pathway and reactivate myocardium.
- Scar, inflammation and electrical heterogeneity facilitate abnormal circuits.
- This mechanism links structural substrate to sustained ventricular tachyarrhythmia.

RE-ENTRY: CONCEPTUAL SEQUENCE




A circulating impulse may repeatedly re-excite myocardium.

Ventricular tachycardia can precede fibrillation

- A re-entry circuit may initiate ventricular tachycardia.
- Multiple or disorganized circuits can evolve into ventricular fibrillation.
- This provides a mechanistic sequence from myocardial remodeling to sudden death.


CONCEPTUAL PATHWAY — SCHEMATIC



Fibrillation terminates effective pump activity

- During fibrillation, ventricular contraction loses coordinated timing.
- Chaotic depolarization does not generate functional forward output.
- The electrical disorder is sufficient to explain rapid collapse.

CONCEPTUAL PATHWAY — SCHEMATIC



The substrate–trigger–endpoint model integrates SCD

- Substrate: Obstructive coronary disease, healed injury or inherited channelopathy.
- Trigger: Spontaneous aberrant depolarization or another disturbance of electrical activity.
- Endpoint: Sustained ventricular rhythm disturbance, often fibrillation.

RELATED SUBSTRATES / COMPONENTS

Substrate


Electrical trigger

Lethal rhythm

Coronary atherosclerotic disease is the leading cause

- Coronary artery disease accounts for most sudden cardiac deaths.
- Its importance reflects both acute ischemic effects and established structural injury.
- Absence of an acute infarct does not remove coronary disease from the differential.

CONCEPTUAL PATHWAY — SCHEMATIC



Sudden death may be the first manifestation of IHD


- A patient may have no previously recognized ischemic heart disease.
- Severe coronary pathology can remain clinically silent until a lethal electrical event.
- This disconnect between symptoms and disease burden is central to the pathology of SCD.

No previous angina or infarct is required for SCD to reveal severe CAD.

Fixed critical coronary stenosis is a typical substrate

- Severe chronic coronary atherosclerosis with fixed critical narrowing.
- Reduced flow reserve predisposes the myocardium to ischemic instability.
- A new occlusive thrombus is not necessary in the typical SCD case.

CORONARY ARTERY CROSS-SECTION — SCHEMATIC



Plaque / narrowed lumen

Acute plaque disruption is a minority finding

- The reported frequency of acute plaque disruption in SCD is 10–20%.
- Most patients therefore lack this particular acute plaque event.
- Atherosclerosis may still be extensive despite the absence of rupture.

ANNUAL CASE ESTIMATES

10–20%

Acute plaque disruption

Most cases

No identified acute plaque disruption

Sudden electrical death does not require new necrosis

- Myocardial irritability may arise from nonlethal ischemia.
- The patient may die before histologic infarction becomes apparent.
- Clinical and pathological findings must not be forced into an acute-MI-only model.

SIDE-BY-SIDE DISTINCTION

Ischemia

May disturb
electrophysiology

Can remain nonlethal
to cells

Infarction

Requires myocardial
cell death

Morphology evolves
over time

Resuscitated SCD often lacks evidence of infarction

- That 80–90% of successfully resuscitated patients show no enzymatic or ECG evidence of myocardial necrosis.
- This statistic applies to the stated resuscitated population, not every sudden death.
- It reinforces the separation between fatal arrhythmia and acute myocardial necrosis.

ANNUAL CASE ESTIMATES


80–90%

No enzyme/ECG evidence of necrosis among
successfully resuscitated patients

Healed remote infarction leaves an arrhythmic substrate

- Healed myocardial infarctions are reported in approximately 40% of SCD cases.
- Residual fibrosis can fragment normal electrical propagation.
- A remote healed injury may be clinically more informative than the absence of fresh necrosis.

CONCEPTUAL PATHWAY — SCHEMATIC



Subendocardial vacuolization signals chronic ischemia

- Vacuolization of subendocardial myocytes as a common finding.
- This morphologic change is interpreted in the text as evidence of severe chronic ischemia.
- It is distinct from diagnosing a fresh transmural myocardial infarct.

Morphology: Subendocardial myocyte vacuolization → chronic ischemic stress.

Three pathological observations can coexist in SCD

- Severe fixed coronary stenoses provide chronic ischemic substrate.
- Healed infarct scars establish prior myocyte injury and fibrosis.
- Chronic subendocardial change may be present without a fresh infarction.

RELATED SUBSTRATES / COMPONENTS

Fixed coronary stenosis

Old myocardial scar

Subendocardial vacuoles

IHD produces several clinical syndromes

- Angina reflects ischemia insufficient to cause infarction.
- Myocardial infarction requires ischemia-associated necrosis.
- Chronic IHD may produce heart failure; SCD may occur across this spectrum.

CATEGORIZED FEATURES

Angina

Acute infarction


Chronic IHD

Sudden cardiac death

Acute infarction can provoke fatal rhythm disturbances

- Myocardial infarction increases irritability and disrupts conduction.
- MI-associated arrhythmias include ventricular tachycardia, fibrillation and block.
- The Robbins discussion places maximal serious arrhythmia risk early after infarction.


CONCEPTUAL PATHWAY — SCHEMATIC



Hypertrophic fibrotic hearts form a second major pattern

- Increasing SCD in hypertrophic, fibrotic hearts without IHD in high-resource countries.
- Hypertension, obesity and cocaine exposure are given as associated contexts.
- The shared substrate is remodeled myocardium capable of unstable electrical conduction.

CONCEPTUAL PATHWAY — SCHEMATIC



Hypertension, obesity and cocaine provide distinct contexts

- Hypertension is linked in the source to hypertrophic and fibrotic cardiac remodeling.
- Obesity is listed among contexts associated with this non-IHD pattern.
- Cocaine is additionally included among non-prescription drug contributors to SCD.

RELATED SUBSTRATES / COMPONENTS

Hypertension

Obesity

Cocaine exposure

Ischemic and nonischemic substrates can converge

- Coronary stenosis favors ischemic electrical instability.
- Hypertrophy and interstitial fibrosis favor disturbed myocardial conduction.
- Both pathways may end in the same fatal ventricular rhythm.

SIDE-BY-SIDE DISTINCTION

Ischemic substrate

Severe coronary stenosis

Chronic ischemic injury

Nonischemic remodeling

Myocardial hypertrophy

Fibrosis without CAD

Age changes the etiologic differential

- Coronary atherosclerosis dominates the overall population burden.
- Younger individuals are more likely to have nonatherosclerotic causes.
- Age directs attention to cardiomyopathy, congenital lesions, myocarditis and inherited electrical disease.

SIDE-BY-SIDE DISTINCTION

Overall population

CAD most frequent

Younger patients

Nonatherosclerotic
causes relatively more
common

Nonatherosclerotic SCD has a broad structural differential

- Dilated or hypertrophic cardiomyopathy can be associated with sudden death.
- Congenital coronary arterial abnormalities and myocarditis are recognized alternatives.
- Mitral valve prolapse and pulmonary hypertension also appear in the Robbins list.

CATEGORIZED FEATURES

Cardiomyopathy

Coronary anomalies

Myocarditis

**MVP / pulmonary
hypertension**

Cardiomyopathy can create an arrhythmogenic myocardium

- Dilated cardiomyopathy is an example of a disease with abnormal myocardial coupling.
- Hypertrophic cardiomyopathy is a recognized structural cause of SCD.
- Both illustrate how altered myocardium can be electrically hazardous.

SIDE-BY-SIDE DISTINCTION

Dilated phenotype

Abnormal intercellular
coupling

Hypertrophic phenotype

Myocardial structural
remodeling

Congenital coronary anomalies belong in younger patients


- Congenital coronary arterial abnormalities are listed causes of SCD.
- They should remain in consideration when conventional atherosclerotic disease is absent.
- The SCD source does not specify individual anatomical variants or their frequencies.

Coronary pathology is not synonymous with atherosclerosis.

Myocarditis couples inflammation to electrical instability

- Inflammatory injury is one of the stated promoters of spontaneous myocyte depolarization.
- Myocarditis is also explicitly listed among nonatherosclerotic causes of SCD.
- Inflammation can therefore provide the electrical substrate even without coronary obstruction.

CONCEPTUAL PATHWAY — SCHEMATIC



Valvular and pulmonary vascular disease also appear

- Mitral valve prolapse is a listed nonatherosclerotic association.
- Pulmonary hypertension is separately included among potential etiologies.
- Robbins does not give a syndrome-specific risk estimate within this SCD passage.

SIDE-BY-SIDE DISTINCTION

Mitral valve prolapse

Listed structural
association

Pulmonary hypertension

Listed
vascular/hemodynamic
association

Catastrophic hemodynamic conditions require separate thought

- Pericardial tamponade and pulmonary embolism are specifically named in the differential.
- Systemic metabolic or hemodynamic alterations also appear among miscellaneous causes.
- Not every rapidly fatal cardiac-related event must share the same antecedent myocardial lesion.

RELATED SUBSTRATES / COMPONENTS

Pericardial tamponade

Pulmonary embolism

Systemic disturbance

Adrenergic agents and stimulants are relevant exposures

- Catecholamines are listed among potential contributors to SCD.
- Cocaine and methamphetamine use.
- An exposure history may be essential when severe coronary atherosclerosis is not demonstrated.

RELATED SUBSTRATES / COMPONENTS

Catecholamines

Cocaine

Methamphetamine

Structural disease and primary electrical disease differ

- Structural diseases produce recognizable myocardial, coronary or valve abnormalities.
- Primary electrical syndromes can cause fatal arrhythmias in the absence of visible structural pathology.
- This distinction determines what clinical history and inherited disease evidence may add.

SIDE-BY-SIDE DISTINCTION

Structural substrate

Coronary disease /
scar / remodeling

Primary electrical substrate

Channel defect;
Structure may appear
normal

Inherited cardiac causes merit focused recognition

- Inherited arrhythmogenic conditions can occur with or without structural abnormality.
- Recognition matters because intervention can prevent some sudden deaths.
- A positive family history or unexplained nonlethal arrhythmia should raise concern.

CONCEPTUAL PATHWAY — SCHEMATIC

Family history / unexplained event



Consider inherited syndrome



Potential preventive intervention

Channelopathies disturb cardiac ion currents

- Mutations affect channel components or proteins required for their function.
- Sodium, potassium and calcium handling are represented Table 12.6.
- Abnormal depolarization or repolarization may predispose to dangerous ventricular rhythms.

RELATED SUBSTRATES / COMPONENTS

Na⁺ current

K⁺ current

Ca²⁺ handling

Different channels contribute to distinct electrical phases

- Channel currents are necessary for the electrical activity that organizes contraction.
- Repolarization changes are exemplified by long- and short-QT syndromes.
- Abnormal intracellular calcium handling is represented by CPVT-associated genes.

RELATED SUBSTRATES / COMPONENTS

Depolarization

Repolarization

Calcium release

QT syndromes illustrate opposite repolarization phenotypes

- Long QT syndrome is characterized by excessive prolongation of repolarization.
- Short QT syndrome is associated with abbreviated repolarization.
- Either phenotype can confer susceptibility to serious ventricular arrhythmia.

SIDE-BY-SIDE DISTINCTION

Long QT

Prolonged
repolarization


Short QT

Abbreviated
repolarization

Long QT syndrome: Clinical phenotype

- QT prolongation may accompany life-threatening ventricular arrhythmias.
- Patients can present with stress-induced syncope or SCD.
- An association with swimming for some forms.

CONCEPTUAL PATHWAY — SCHEMATIC



Long QT: Potassium-channel loss of function

- KCNQ1 loss of function appears Table 12.6.
- KCNH2 loss of function is another listed cause.
- Both are examples of impaired potassium-channel function associated with prolonged QT.

SIDE-BY-SIDE DISTINCTION

KCNQ1

K⁺ channel; Loss of function

KCNH2

K⁺ channel; Loss of function

Long QT: Increased sodium-current mechanisms

- SCN5A gain of function is listed as a long-QT mechanism.
- CAV3 is included in the table as affecting caveolin and sodium current.
- Different molecular changes can converge on the same clinical repolarization phenotype.

SIDE-BY-SIDE DISTINCTION

SCN5A

Na⁺ current; Gain of function


CAV3

Caveolin / Na⁺ current; Gain of function

Short QT syndrome: Abbreviated repolarization

- The source describes an abnormally short repolarization interval.
- Presentations may include palpitations, syncope or sudden death.
- A shortened QT phenotype is not benign simply because repolarization is faster.

CONCEPTUAL PATHWAY — SCHEMATIC



Short QT: Potassium-channel gain of function

- The table lists KCNQ1 gain-of-function mutations.
- KCNH2 gain of function is also listed.
- The opposite functional direction in these genes contrasts with long-QT disease.

SIDE-BY-SIDE DISTINCTION

KCNQ1

K⁺ channel; Gain of function

KCNH2

K⁺ channel; Gain of function

Brugada syndrome: Recognizable ECG phenotype

- ST-segment elevation and a right bundle-branch-block pattern.
- Structural heart disease may be absent.
- Syncope or SCD classically occurs during rest, sleep or after a large meal.

CONCEPTUAL PATHWAY — SCHEMATIC

Characteristic ECG changes



Often no structural lesion



Rest / sleep events

Brugada: Source-listed loss-of-function genes


Gene / syndrome	Channel / trigger	Feature / functional change
SCN5A	Na ⁺	Loss of function
CACNB2b	Ca ²⁺	Loss of function
SCN1b	Na ⁺	Loss of function

SCN1b is listed for sodium-channel loss of function.

CPVT: Adrenergically triggered ventricular arrhythmia

- Catecholaminergic polymorphic ventricular tachycardia often presents in childhood.
- Life-threatening arrhythmias are associated with adrenergic stimulation or stress.
- CPVT lacks characteristic resting ECG changes.

CONCEPTUAL PATHWAY — SCHEMATIC



CPVT: Altered diastolic calcium release

- RYR2 gain of function affects diastolic calcium release.
- CASQ2 loss of function is another source-listed cause.
- Both appear under the CPVT phenotype despite differing molecular direction.

SIDE-BY-SIDE DISTINCTION

RYR2

Diastolic Ca²⁺ release

Gain of function

CASQ2

Diastolic Ca²⁺ release

Loss of function

Trigger patterns discriminate inherited syndromes

Gene / syndrome	Channel / trigger	Feature / functional change
Long QT	Stress; Swimming in some forms	QT prolonged
Short QT	No trigger specified in text	QT abbreviated
Brugada	Rest / sleep / large meals	Characteristic ECG
CPVT	Adrenergic stress	No characteristic ECG change

CPVT is linked to childhood arrhythmias with adrenergic stress.

Gain versus loss of function is phenotype-specific

- The same gene can be associated with different electrical syndromes.
- For KCNQ1 and KCNH2, loss of function appears with long QT and gain of function with short QT.
- A gene name alone does not establish mutation-level function or a patient phenotype.

SIDE-BY-SIDE DISTINCTION

Loss of K⁺ function

KCNQ1 / KCNH2

Long-QT association

Gain of K⁺ function


KCNQ1 / KCNH2

Short-QT association

Family history and unexplained arrhythmia change evaluation

- Some inherited electrical diseases are not evident by gross structural inspection.
- Genetic testing with a positive family history or unexplained nonlethal arrhythmia.
- Genetic findings must be interpreted in relation to syndrome and mutation effect.

CONCEPTUAL PATHWAY — SCHEMATIC



A structurally normal heart does not exclude arrhythmic SCD


- Primary electrical syndromes can produce lethal arrhythmias with no recognizable structural disease.
- Brugada is explicitly described as potentially lacking structural heart disease.
- The absence of a gross lesion cannot independently rule out an inherited channelopathy.

Anatomically normal ≠ electrically normal.

Prevention targets patients at risk of lethal rhythms

- Pharmacological interventions improve prognosis in vulnerable patients.
- Implantable automatic cardioverter-defibrillators are another preventive strategy.
- The supplied source does not provide drug selection, device eligibility criteria or guideline thresholds.


CONCEPTUAL PATHWAY — SCHEMATIC



An implantable defibrillator senses and terminates VF

- An implanted device can detect episodes of ventricular fibrillation.
- It responds electrically to counteract the arrhythmia.
- Its purpose is to interrupt a lethal rhythm, not reverse coronary atherosclerosis or myocardial scar.

CONCEPTUAL PATHWAY — SCHEMATIC



Case: Death without documented acute infarction


- A person collapses unexpectedly and is successfully resuscitated.
- Evaluation shows severe chronic coronary stenoses but no enzyme or ECG evidence of myocardial necrosis.
- Question: Does the absence of infarction evidence make an arrhythmic coronary mechanism unlikely?

Interpret the coronary substrate separately from evidence of new necrosis.

Case interpretation: Electrical instability can precede necrosis

- No: Chronic CAD is the leading substrate for SCD in the Robbins discussion.
- Nonlethal ischemia and healed myocardial injury can still trigger dangerous ventricular rhythms.
- This pattern matches the textbook observation that many resuscitated patients lack infarction evidence.

CONCEPTUAL PATHWAY — SCHEMATIC



Case: A young person with stress-related syncope

- A child experiences recurrent syncope associated with adrenergic stress.
- A characteristic resting ECG signature is absent; Structural assessment is unrevealing.
- Question: Which source-listed inherited syndrome strongly fits the trigger pattern?

Use trigger context and electrical phenotype; Do not invent ECG criteria.

Case interpretation: Consider CPVT

- CPVT is associated with life-threatening stress-triggered arrhythmias, often presenting in childhood.
- The lack of a characteristic resting ECG change.
- The table links CPVT to RYR2 and CASQ2 abnormalities of diastolic calcium release.

CONCEPTUAL PATHWAY — SCHEMATIC

Childhood + stress-triggered events



CPVT pattern



RYR2 / CASQ2 examples

Clinicopathologic recognition: Five useful distinctions

- An acute plaque rupture is not necessary to establish coronary-associated SCD.
- Healed infarction and chronic ischemic change can be clues even without fresh necrosis.
- In younger patients, congenital, myocardial and inherited electrical causes become more important.
- A structurally normal heart may still harbor a serious channelopathy.

CATEGORIZED FEATURES

**Fixed stenosis ≠
rupture**

Fibrosis ≠ fresh MI

**Younger ≠ usual CAD
pattern**

**Normal anatomy ≠
normal currents**

Core concepts: The substrate matters more than a single lesion

- SCD is an unexpected terminal event; Ventricular fibrillation is the characteristic electrical mechanism.
- Coronary atherosclerosis, often without acute plaque rupture or necrosis, is the leading substrate.
- Myocyte irritability, disturbed cell-to-cell coupling and re-entry connect pathology to fatal rhythm.
- Structural nonatherosclerotic disease and inherited channelopathies broaden the differential.

Identify the substrate, explain the rhythm and interpret the morphology.

Primary references

- Robbins, Cotran & Kumar: Pathologic Basis of Disease. 11th edition (2026). Chapter 12, The Heart; Sudden Cardiac Death, p. 504.
- Supporting adjacent text: Arrhythmias, pp. 503–504; ischemic heart disease / myocardial infarction, pp. 492–503.
- Inherited arrhythmogenic gene associations: Robbins Table 12.6 (modified there from Cerrone M, Priori SG. Eur Heart J. 2011;32:2109–2118).